

TECHNICAL DATA SHEET

OUTSTANDING FEATURES

- ◆ 5 Digit Rate Display, 8 Digit Totalizer Display.
- ◆ Local Magnetic or Remote Reset.
- ◆ 4-20mA Analog Output.
- ◆ Powered From Battery, DC Supply, 4-20mA Output Loop, or AC Line.
- ◆ 20 Pt. Linearization Option.
- ◆ Isolated Scaled Pulse Output.
- ◆ Alarm Output for Rate or Total.
- ◆ Windows® Configuration Program.
- ◆ RS 232 Port for Configuration and Monitoring.
- ◆ Diagnostics for Pulse, Alarm and Analog output.
- ◆ Password Protection for Menu and Reset.

GENERAL DESCRIPTION

Featuring 5 digits of rate and 8 digits of total, the HIT-2A is a DC, AC, loop or battery powered indicator capable of accepting magnetic pickup, DC pulse or switch closure inputs. The unit can be ordered with an optional loop powered 4-20mA output. The HIT-2A uses the 4-20mA loop to provide power when this output is used.

SPECIFICATIONS

Power Supply:

BATTERY POWERED

Supplied with 2 C-size Lithium battery pack.

Battery Life Expectancy*	
Power Supply Option	RUN TIME— continuous operation
A	6 years minimum.
B, C, and AC	10 years minimum.
*Life expectancy without pulse or alarm outputs selected.	

DC POWER INPUT

Voltage: 8 to 30 VDC.
Current: Less than 4 mA.
Supplied with 1 C-size lithium battery.
Protection: Reverse Polarity Protection
Loop Burden: 8V maximum.

AC POWER INPUT UNIVERSAL

Voltage: 100-240 VAC @ 0.15A 50/60 Hz.



Display:

RATE DISPLAY: (SELECTABLE DECIMAL)

5 Digits (99999), 0.5" High, Display updates once every two seconds.

Rate Descriptors: /MIN, /HR, / DAY.

10 segment bar graph display for rate trend.

TOTALIZER DISPLAY: (SELECTABLE DECIMAL)

8 Digits (99999999), 0.26" High.

Totalizer Descriptors: GAL, LIT, FT3, M3, BBL "blank" (for other descriptors).

LOW BATTERY WARNING DISPLAY

(Displays with approx. 10% of the power remaining)

Pulse Output:

The pulse output advances with the least significant digit of the totalizer.

Opto-isolated open collector transistor: 100 VDC, 100 mA.

Pulse Duration: Selectable (see below).

Pulse Output Rate: Selectable (see below).

Pulse output divider: User selectable,) 1,) 10,) 100 or OFF. **NOTE:** Select OFF for max. battery life.

SPEED (HZ)	1	2	4	8
Min. on/off (msec)	500	250	125	62.5

Alarm Output:

Configurable for rate or total.

Opto-isolated open collector transistor: 100 VDC, 100 mA.

Environmental:

OPERATING TEMPERATURE

-4°F (-20°C) to + 158°F (70°C)

HUMIDITY

0 - 90% Non-condensing

Accuracy:

0.01% Reading, ± 1 count

Temperature Drift: 50 ppm/°C
Worst Case

Inputs:

MAGNETIC PICKUP INPUT

Frequency Range: 0.2 to 5000 Hz

Trigger Sensitivity: 30 mV p-p

OPTO-ISOLATED DC PULSE INPUT

High (logic 1): 4-30 VDC

Low (logic 0): Less than 1 VDC

Minimum Current: 1 mA

Frequency Range: 0 to 5000 Hz

Min. Pulse Width: 0.1 msec

CONTACT CLOSURE INPUT (CONTACT CLOSURE TO COMMON)

Internal Pullup Resistor: 220 K Ω to +3.3 VDC

High (logic 1): Open or 4-30 VDC

Low (logic 0): Less than .5 VDC

RESET INPUT (CONTACT CLOSURE TO COMMON)

Internal Pullup Resistor: 100 K Ω to +3.3 VDC

High (logic 1): Open or 4-30 VDC

Low (logic 0): Less than .5 VDC

With local resettable external magnet or optional remote reset.

K-FACTOR

Range: 0.001 to 99999999

Decimal Point

Locations: XX.XXX to XXXXX

20 POINT LINEARIZATION OPTION

This feature allows the user to enter up to 20 different frequencies with 20 different corresponding K-Factors to improve flowmeter accuracy to $\pm 0.1\%$.

Analog Output Option:

Type: 4-20 mA follows rate display,

Two Wire hookup

Accuracy: 0.02% Full Scale @ 20°C

Temperature Drift: 40 ppm/°C

Reverse Polarity Protected

NOTE: The Hit-2A can use the 4-20 mA loop power as its power source when this option is used.

Approvals: CE approval (optional).

ORDERING INFORMATION

Basic Model Number HIT-2A - (A) - (B) - (C) - (D) - (E) - (F)

Series:

A. Enclosure Style:

- 2 NEMA 4X Enclosure (Hit-2A behind clear cover)
- 3 Explosion-Proof Housing. Class I, Division I, Groups B, C & D. Class II, Division I, Groups E, F & G.
- 3A ATEX Exd Enclosure.
- P Panel Mount Enclosure. 1/4 DIN.
- PD Panel Mount Enclosure with Clear Door and Lock.
- 4 Nema 1 Enclosure. HIT-2A Mounted to the outside of

B. Input Power:

- A Internal Batteries, two supplied. (Option A not available for use w/ Redi-Pulse coil)
- B External Power Supply (8 to 30 VDC)
- AC Universal 100-240 VAC @ 0.15A 50/60 Hz
- X Enter (X) if loop powered analog output option C or D below is selected.

C. Loop Powered Analog Output:

- C Loop Powered with 4-20mA Output (8 to 30 VDC)
- D Loop Powered with 4-20mA Output and 2 internal batteries

D. Options:

- L 20 Point Linearization
- RR Remote Reset
- AL Low Alarm* opto isolated open collector
- AH High Alarm* opto isolated open collector
- *Note: Either low or high alarm available, not both.

E. Mounting:

- F Nema 4x Style 2 enclosure mounted on turbine. Must be used with "X" riser turbine option.
- FHT 8" long temperature riser for Nema 4x Style 2 enclosure mounted on turbine. Required when fluid temperature exceeds 140 deg. F. Must be used with "X" riser turbine option.
- FX Explosion-proof Style 3 enclosure mounted on turbine. Must be used with "X" riser option on turbine.
- FXHT 8" long temperature riser for Explosion-Proof Style 3 enclosure mounted on turbine. Required when temperatures exceed 140 deg. F. Must be used with "X" riser turbine option.
- NP Nema 4X enclosure pipe mounting kit 2" pipe or smaller. Specify if pipe is vertical or horizontal.

F. Special Features: (Multiple Options Available)

- CE CE Mark required for Europe.
- SP Any Special Features that are not covered in the Model Number. Use a written description of the -SP.

Notes:

1. Opto-isolated open collector transistor is standard with all units.
2. A local reset magnet is standard with all units except if remote reset option is selected.
3. Two batteries are required for battery powered units. One battery is required for all other power options to retain total display if power fails.

Accessories:

- » H1TC Spare Battery: Tadiran P/N TL2200/S. 3.6 V 5500mAh or equal.
- » 115-24 Universal 100-240 VAC to 24 VDC power supply.
Note: To mount in explosion-proof enclosure, select (3) above under enclosure style. Power supply may be remote.
- » Windows based setup disk and 6 foot communication cable.

H **HOFFER FLOW CONTROLS, INC.**
107 Kilty Hawk Lane, P. O. Box 2145, Elizabeth City, NC 27906-2145
800-628-4584 252-331-1997 FAX 252-331-2886
www.hofferflow.com email: info@hofferflow.com

The specifications contained herein are subject to change without notice and any user of said specifications should verify from the manufacturer that the specifications are currently in effect. Otherwise, the manufacturer assumes no responsibility for the use of specifications which may have been changed and are no longer in effect.

The quality system covering the design, manufacture and testing of our products is certified to International Standard ISO 9001.



ISO9001
Registered Company